Service Manual

Digital Power Amplifier

DPA-300D/600D

inter M

CONTENTS

Specifications 1
Electrical Parts List 2
Top and Bottom View of P.C. Board 17
Block Diagram 29
Schematic Diagram 31
Wiring Diagram 47
Exploded View of Cabinet & Chassis / Mechanical Parts List 50

SPECIFICATIONS

		DPA-300D	DPA-600D
Rated Output Power (THD 0.1%, AES17)		300W x 2	600W x 2
Peak Power		350W/CH	680W/CH
Output Level/Impedance		100V/33.3Ω	100V/16.6Ω
		70V/16.3Ω	70V/8.1Ω
		49V/8Ω	69.3V/8Ω
Input Sensitivity		1V/10kΩ	
THD (AES17)	Rated Power	Less than 0.1%	
	1/3 Power	Less than 0.03%	
S/N (20kHz LPF)		More than 103dB	
Frequency Response (1W, ±3dB)		50Hz~20kHz	
Operating Temperature		-10°C ~ +40°C	
Operating Power		120VAC, 60Hz, 220-240VAC, 50/60Hz 24VDC	
Power Consumption (1/8 Power)		130W	250W
Weight (SET)		7.1kg/15.7lb	8.1kg/17.9lb
Dimensions (SET)		482(W) x 88(H) x 397(D)mm 19(W) x 3.5(H) x 15.6(D)in	482(W) x 88(H) x 450(D)mm 19(W) x 3.5(H) x 17.7(D)in

* Design and specification are subject to be changed for the improvement of product quality without pre notice.

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
DPA-300D AMP			
R170-171 R279-280			
R381	104234	"R10J/A,10"	10
R219-220 R319-320	104274	"R2KJ/A,2K"	2K
R227-228 R327-328	104347	"R56KJ/A,56K"	56K
R237-238 R337-338	104454	"R10J/1W/MF/T,10 1W"	10 1W
R267-268	104673	"R56J/2W/MO/T,56 2W"	56 2W
R274-275 R374-375	104745	"R25J/5W/CE,25"	25
"C112-113 C118-119			
C139-140 C215 C242			
C246-247 C315"	105508	"EC47U25M/RG/T,47/25"	47/25
C221	105511	"EC47U50M/SG/T,47/50"	47/50
C240-241 C243-244			
C262-263	105585	"EC470U100M/NXB,470/100"	470/100
C225-226 C325-326	105857	"MA0.033U100J/T,0.033/100(M)"	0.033/100(M)
C223-224 C323-324	105909	"MA0.1U250J/DEM/T,0.1/250(M)"	0.1/250(M)
C216-217 C316-317	105910	"MA0.1U250K/DEM/T,0.1/250(M)"	0.1/250(M)
C290-291 C390-391	105919	"MA0.068U250J/DEM/T,0.068/250(M)"	0.068/250(M)
C203-206 C303-306	105929	"MA2200P50M/MKS/T,2200P50(M)"	2200P50(M)
"TP106 TP111			
TP205-207			
TP209 TP305-307			
TP310 TP312"	106871	"TP/TP00325-21/T,TP00325-21"	TP00325-21
CN2	110495	"05P/B5P-VH/3.96/110495,B05PVH-05P"	B05PVH-05P
CP1-3	111330	"02P/53014/2,53014-02P"	53014-02P
CN201	111358	"03P/LW-5267/2.5,LW5267-03P"	LW5267-03P
CN1	111360	"05P/LW-5267/2.5,LW5267-05P"	LW5267-05P
CN901	111365	"10P/LW-5267/2.5,LW5267-10P"	LW5267-10P
CN101	111371	"16P/LW-5267/2.5,LW5267-16P"	LW5267-16P
SW201	112022	"SL/JSS-2208A,JSS-2208A"	JSS-2208A
Q211	118627	"PNP/KRA303/USM,KRA303"	KRA303
"Q104-105 Q109-110			
Q215 Q217			
Q230 Q315 Q317			
Q330 Q902 Q906"	118638	"NPN/KRC403/USM,KRC403"	KRC403
Q201	118643	"NPN/KTC4375-Y/SOT89,KTC4375-Y"	KTC4375-Y
Q213	118657	"PNP/KTA1666/SOT89,KTA1666"	KTA1666
Q214 Q216 Q219			
Q314 Q316 Q319	118663	"PNP/2N3906S/SOT23,2N3906S"	2N3906S
Q101-102 Q106-107			
Q208 Q210 Q212			
Q218 Q308 Q310	118672	"NPN/2N3904/SOT23,2N3904"	2N3904
IC202	118724	"7805/KIA/D-PAK,7805"	7805
IC101-106	118730	"NJM072M/DMP08P,NJM072M"	NJM072M
IC302	118926	"74HC00/SOP14P,74HC00"	74HC00
"D103-104 D106			
D109-110 D112-114			
D204 D211-212 D214			
D219-220 D304 D314			
D901-902"	119190	"D/BAS21/SOT23,BAS21"	BAS21
D101-102 D105			
D107-108 D111	119196	"D/BAV99/SOT23,BAV99"	BAV99
D205-208 D215-218			
D305-308 D315-318	119203	"D/MURS120T3/DO214AA,MURS120T3"	MURS120T3
LD101 LD204	119236	"LD/G/1608S/LTST-C190TGKT,LTST-C190TGKT"	LTST-C190TGKT
R233-236 R333-336	119346	"R10J/2012,10"	10
R215-216 R241 R256			

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
R315-316 R341 R356 "R122 R126 R148 R152 R201-202 R211-212 R248 R272 R278 R301-302 R311-312 R348 R372"	119353	"R100J/2012,100"	100
"R105-106 R114-117 R132-133 R141-144 R225-226 R284 R295 R297 R325-326 R351-353 R397 R905-906 R912-913"	119362	"R1KJ/2012,1K"	1K
R118 R123 R145 R149 R155-158 R907 R914	119367	"R10KJ/2012,10K"	10K
R159-160	119370	"R100KJ/2012,100K"	100K
R269-270 R369-370	119401	"R12KJ/2012,12K"	12K
R213-214 R313-314	119405	"R120KJ/2012,120K"	120K
R903 R910	119420	"R150J/2012,150"	150
R101-102 R128-129	119435	"R150KJ/2012,150K"	150K
R121 R147	119455	"R1.8KJ/2012,1.8K"	1.8K
R109 R111 R136 R138 R108 R110 R135	119466	"R180KJ/2012,180K"	180K
R137 R902 R909 R296 R203-204 R294	119473	"R2KJ/2012,2K"	2K
R303-304	119499	"R22KJ/2012,22K"	22K
R242 R266 R342	119502	"R220KJ/2012,220K"	220K
R113 R140 R154 R223-224	119548	"R3KJ/2012,3K"	3K
R323-324 "R107 R125 R134 R151 R246 R346 R901 R908"	119576	"R3.3KJ/2012,3.3K"	3.3K
R290 R390 R264 R285 R287	119580	"R33KJ/2012,33K"	33K
R292 R385 R387 R392 "R120 R127 R146 R153 R209-210 R265 R286 R288 R293 R309-310 R386 R388 R393"	119590	"R3.6KJ/2012,3.6K"	3.6K
R904 R911 R229-232 R282-283	119605	"R3.9KJ/2012,3.9K"	3.9K
R329-332 R382-383 R240 R243 R250	119617	"R47J/2012,47"	47
R340 R343 R350	119625	"R4.7KJ/2012,4.7K"	4.7K
R247 R347 R221-222 R271	119630	"R47KJ/2012,47K"	47K
R321-322 R371 R4 R103-104 R124 R130-131 R150	119635	"R470KJ/2012,470K"	470K
R244-245 R344-345	119645	"R4.7J/2012,4.7"	4.7
R112 R139	119670	"R560J/2012,560"	560
C219	119689	"R6.2KJ/2012,6.2K"	6.2K
C126 C239	119707	"R6.8KJ/2012,6.8K"	6.8K
	119747	"R8.2KJ/2012,8.2K"	8.2K
	119949	"R4.3KJ/2012,4.3K"	4.3K
	120237	"CE0.001U50J/3216,0.001U"	0.001U
	120247	"CE0.1U50Z/2012,0.1U"	0.1U

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
C115 C127-128 C142 C151-152 C230-231 C330-331	120251	"CE1U50Z/2012,1U"	1U
C117 C144 C228-229 C245 C269 C328-329	120348	"CE4.7U16M/3216,4.7/16"	4.7/16
C116 C143	120349	"CE10P50J/1608,10P"	10P
C104-105 C108 C131-132 C135 C153-154 C372	120352	"CE100P50J/2012,100P"	100P
C102-103 C129-130	120381	"CE330P50J/2012,330P"	330P
C110-111 C137-138	120389	"CE47P50J/2012,47P"	47P
C107 C134 C201-202 C301-302	120391	"CE470P50J/2012,470P"	470P
"C114 C120-125 C141 C145-150 C218 C220 C232 C248-251 C270-271 C318 C332 C370-371 C373"	120421	"CE0.1U50K/2012,0.1U"	0.1U
FB1-2 FB201-202 FB301-302	123776	"80OHM/BEAD/123776,80OHM"	80OHM
C237-238 C255-256 C260-261 C352	126494	"CE0.01U250K/2012,0.01U"	0.01U
C207-208 C307-308	126495	"CE0.001U250J/2012,0.001U"	0.001U
C213-214 C313-314	126715	"EC10U50M/RD,10/50"	10/50
C227 C327	127070	"EC100U10M/SHL/T,100/10 NP"	100/10 NP
D210	127303	"ZD/15V/Z02W/SOT23,15V"	15V
FB3	127462	"120OHM/BEAD/127462,120ohm"	120ohm
C106 C133	127554	"EC2.2U50M/NXB/T,2.2/50"	2.2/50
IC205 IC305	128200	"LM26CIM5-TPA/SOT23-5,LM26CIM5-TPA"	LM26CIM5-TPA
CON101	128201	"TER/BL/ME030-350/06H/128201,TERMINAL06P"	TERMINAL06P
Q103 Q108 Q901 Q904-905 Q908	129509	"N/PMBFJ112/SOT23,PMBFJ112"	PMBFJ112
C267 C366	129534	"CE0.01U250J/3216,0.01U250"	0.01U250
IC203	129536	"79L05F/KIA/SOT89,KIA79L05F"	KIA79L05F
R276-277 R376-377	129577	"R4.7KJ/2W/MF/T,4.7K 2W"	4.7K 2W
LD202 LD302	129968	"LD/R/1608/BL-HUE36A,BL-HUE36A"	BL-HUE36A
LD201 LD301	130293	"LD/Y/1608/BL-HKB36A,BL-HKB36A"	BL-HKB36A
Q204-207 Q304-307	130597	"N/IRFB5620PBF/TO220,IRFB5620PBF"	IRFB5620PBF
IC201 IC301	131763	"IRS2052MPBF/QFN48P/2,IRS2052MPBF"	IRS2052MPBF
CON201	132912	"TER/OQ0455510000G/04H/132912,TERMINAL04P"	TERMINAL04P
C109 C136	133535	"MA0.18U63J/CEM/T,0.18/63(M)"	0.18/63(M)
IC204 IC304	133640	"LM26CIM5-PHA/SOT23-5,LM26CIM5-PHA"	LM26CIM5-PHA
L201-202 L301-302	2001370	"47UH/37/2001370,47uH"	47uH
H4 H16	2001390	"HS/2001390/67,Heat sink"	Heat sink
DPA-300D FRONT			
IC902	103384	"PC/LTV847,LTV847"	LTV847
VR901	104992	"203A/09/RK09S1110011,20KA"	20KA
VR1-2	105055	"203A/09/RK09K11N0005,20KA"	20KA
CN1002	111360	"05P/LW-5267/2.5,LW5267-05P"	LW5267-05P
AN901	111365	"10P/LW-5267/2.5,LW5267-10P"	LW5267-10P
AN101	111371	"16P/LW-5267/2.5,LW5267-16P"	LW5267-16P
SW1	112178	"PW/SDDL1PASL051,SDDL1PASL051"	SDDL1PASL051
BK1-2	113528	"BK/113528,Bracket"	Bracket
LIM101-103	114982	"LIMITER/5.5/11.5/114982,11.5mm"	11.5mm
LIM1-8	114983	"LIMITER/5.5/14.7/114983,14.7mm"	14.7mm

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
LIM107	114985	"LIMITER/5.5/8/114985,8mm"	8mm
Q1-4 Q13-18 Q25-26			
Q901-904 Q1001-1002	118663	"PNP/2N3906S/SOT23,2N3906S"	2N3906S
Q9-10	118672	"NPN/2N3904/SOT23,2N3904"	2N3904
IC1-2 IC901	118730	"NJM072M/DMP08P,NJM072M"	NJM072M
D5-8	119190	"D/BAS21/SOT23,BAS21"	BAS21
D1-2 D901-906			
D1001-1003	119196	"D/BAV99/SOT23,BAV99"	BAV99
R21-22 R907	119362	"R1KJ/2012,1K"	1K
R13-14	119366	"R10KJ/1608,10K"	10K
R49-50 R905-906	119367	"R10KJ/2012,10K"	10K
R37-38 R1001	119393	"R120J/2012,120"	120
R9-10 R33-34 R910	119401	"R12KJ/2012,12K"	12K
R901-902	119455	"R1.8KJ/2012,1.8K"	1.8K
R1003 R1006	119495	"R2.2KF/3216,2.2K 1%"	2.2K 1%
R5-6 R41-42 R1002	119499	"R22KJ/2012,22K"	22K
R911-914	119527	"R2.7KJ/2012,2.7K"	2.7K
R915-918	119548	"R3KJ/2012,3K"	3K
R1-2 R25-26 R908	119580	"R33KJ/2012,33K"	33K
R29-30 R909	119605	"R3.9KJ/2012,3.9K"	3.9K
R1004	119620	"R470J/2012,470"	470
R919 R921 R923 R925	119625	"R4.7KJ/2012,4.7K"	4.7K
R45-46 R920 R922			
R924 R926	119630	"R47KJ/2012,47K"	47K
R17-18	119711	"R68KJ/2012,68K"	68K
R903-904	119747	"R8.2KJ/2012,8.2K"	8.2K
C1-2	120348	"CE4.7U16M/3216,4.7/16"	4.7/16
C13-14 C903-904 C908	120352	"CE100P50J/2012,100P"	100P
C901-902	120381	"CE330P50J/2012,330P"	330P
C9-10 C907	120391	"CE470P50J/2012,470P"	470P
C17-20 C25-26			
C909-910 C1001	120421	"CE0.1U50K/2012,0.1U"	0.1U
LD1004	126148	"LD/B/3T/SLB1381N-UZ,SLB1381N-UZ"	SLB1381N-UZ
C911	126494	"CE0.01U250K/2012,0.01U"	0.01U
C905	127554	"EC2.2U50M/NXB/T,2.2/50"	2.2/50
LD1 LD5	129892	"LD/R/3T/BL-B4541,BL-B4541"	BL-B4541
LD2 LD6 LD1002	130016	"LD/Y/3T/BL-3141-AA-AV,BL-3141-AA-AV"	BL-3141-AA-AV
LD3-4 LD7-8			
LD1001 LD1003	130018	"LD/G/3.1T/BL-B2141,BL-B2141-AA-AV-T05"	BL-B2141-AA-AV-T05
CON901	130135	"TER/OQ0812510000G/08H/130135,TERMINAL08P"	TERMINAL08P
LD901-904	130293	"LD/Y/1608/BL-HKB36A,BL-HKB36A"	BL-HKB36A
AN1002 CN1001	133349	"05P/ASSY/2.5/133349,ASS'Y-05P"	ASS'Y-05P
C5-6 C906	133535	"MA0.18U63J/CEM/T,0.18/63(M)"	0.18/63(M)
DPA-300D SMPS			
U9	103061	"7812/KIA,7812"	7812
VAR1-2	103422	"ZNR/361/INR14D361,360V"	360V
TH1	103435	"10/M/10A/160T/-40~180C/DSC-10D-30,10 ohm"	10 ohm
R57	104453	"R750KJ/1/2W/MF/A,750K 1/2W"	750K 1/2W
R3 R5	104518	"R10J/2W/MO/T,10 2W"	10 2W
R77 R97-98 R115			
R162-163	104537	"R10KJ/2W/MO/T,10K 2W"	10K 2W
R100 R111	104543	"R0.1J/3W/MO,0.1 3W"	0.1 3W
R471	104567	"R15KJ/1W/MO/T,15K 1W"	15K 1W
R160-161 R164-167	104592	"R220J/2W/MO/T,220 2W"	220 2W
R72	104634	"R330J/2W/MO/T,330 2W"	330 2W
C62 C66 C68	105351	"EC220U50M/RD,220/50"	220/50

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
C4 C7 C11 C14 C55			
C70 C73 C81	105462	"EC22U25M/RG/T,22/25"	22/25
C74	105463	"EC22U50M/SHL/T,22/50"	22/50
C203 C206	105508	"EC47U25M/RG/T,47/25"	47/25
C121	105548	"EC4.7U50M/RG/T,4.7/50"	4.7/50
C71 C103 C113 C116	105625	"EC2200U35M/RD,2200/35"	2200/35
C46 C202	105793	"CE2200P250M/AC,2200P250"	2200P250
C117	105825	"MA0.1U200J/T,0.1/200(M)"	0.1/200(M)
C455-456	105909	"MA0.1U250J/DEM/T,0.1/250(M)"	0.1/250(M)
C461	105933	"MA3900P250J/CEM/T,3900P250(M)"	3900P250(M)
CX1 CX3	105992	"MA1U275K/AC,1/275(M)"	1/275(M)
TP1-10 TP16 TP19			
TP201 TP209	106871	"TP/TP00325-21/T,TP00325-21"	TP00325-21
CN5	110495	"05P/B5P-VH/3.96/110495,B05PVH-05P"	B05PVH-05P
CN4	110850	"TER/BL/010/02H/110850,TERMINAL02P"	TERMINAL02P
CN1-2	111360	"05P/LW-5267/2.5,LW5267-05P"	LW5267-05P
F3	111579	"FUSE/GF-205B,GF-205B"	GF-205B
JK1	111737	"ACIN/SS-7B-1-09,AC IN"	AC IN
F1	112598	"20/5A/250V/T/KUCJ/112598,T5A/250V"	T5A/250V
Q13	118627	"PNP/KRA303/USM,KRA303"	KRA303
Q20	118657	"PNP/KTA1666/SOT89,KTA1666"	KTA1666
PC1-6 PC9 PC16	118872	"PC/LTV817B,LTV817B"	LTV817B
D1 D10 D46-47	119171	"D/1N4148/SOT23,1N4148"	1N4148
D21 D43	119194	"D/KDS184/SOT23,KDS184"	KDS184
D204	119210	"ZD/10V/BZX84C/SOT23,10V"	10V
R147 R150	119341	"R1J/3216,1"	1
R36 R56 R156 R207	119346	"R10J/2012,10"	10
R63 R175	119348	"R10J/3216,10"	10
R70	119353	"R100J/2012,100"	100
R69 R138-139			
R148-149	119362	"R1KJ/2012,1K"	1K
"R2 R66-67 R89 R108			
R129 R134 R136 R154			
R177 R403 R405 R461"	119367	"R10KJ/2012,10K"	10K
R78	119373	"R1MJ/2012,1M"	1M
R201-202	119374	"R1MJ/3216,1M"	1M
R48 R61	119388	"R12J/2012,12"	12
R76 R116 R462	119396	"R1.2KJ/2012,1.2K"	1.2K
R15 R79	119401	"R12KJ/2012,12K"	12K
R113	119405	"R120KJ/2012,120K"	120K
R463	119408	"R1.3KF/2012,1.3K 1%"	1.3K 1%
R99	119408	"R1.3KJ/2012,1.3K"	1.3K
R155	119425	"R1.5KJ/3216,1.5K"	1.5K
R92 R131 R135 R490	119428	"R15KJ/2012,15K"	15K
R128 R140	119436	"R150KJ/3216,150K"	150K
R124 R126-127			
R132-133 R159	119473	"R2KJ/2012,2K"	2K
R91	119476	"R20KJ/2012,20K"	20K
R205	119487	"R22J/2012,22"	22
R114	119492	"R220J/2012,220"	220
R82 R101	119497	"R2.2KJ/2012,2.2K"	2.2K
R25	119499	"R22KJ/2012,22K"	22K
R27	119531	"R27KJ/2012,27K"	27K
R158	119548	"R3KJ/2012,3K"	3K
R10 R110	119576	"R3.3KJ/2012,3.3K"	3.3K
R33-34	119581	"R33KJ/3216,33K"	33K
R93	119586	"R330KJ/2012,330K"	330K

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
R469	119625	"R4.7KJ/2012,4.7K"	4.7K
R7-8 R137	119630	"R47KJ/2012,47K"	47K
R19-20 R203-204	119631	"R47KJ/3216,47K"	47K
R54 R144-145	119636	"R470KJ/3216,470K"	470K
R117	119644	"R4.7J/3216,4.7"	4.7
R68 R130 R172	119655	"R5.1KJ/2012,5.1K"	5.1K
R125	119658	"R51KJ/2012,51K"	51K
R206	119670	"R560J/2012,560"	560
R105	119689	"R6.2KJ/2012,6.2K"	6.2K
R64	119701	"R680J/2012,680"	680
R152	119727	"R750J/2012,750"	750
R104	119732	"R7.5KJ/2012,7.5K"	7.5K
R174	119770	"R100KF/3216,100K 1%"	100K 1%
R103	119822	"R68KF/3216,68K 1%"	68K 1%
R87	119823	"R75KF/2012,75K 1%"	75K 1%
R118 R176 R183			
R402 R404	119955	"R51J/2012,51"	51
R40 R71 R80			
R178 R409	120063	"R0J/3216,0"	0
C118	120235	"CE0.001U50J/2012,0.001U"	0.001U
C115	120247	"CE0.1U50Z/2012,0.1U"	0.1U
C5-6 C31-32 C49			
C86-87 C96 C111			
C114 C133	120251	"CE1U50Z/2012,1U"	1U
C109	120275	"CE2200P50K/2012,2200P"	2200P
C108	120283	"CE0.22U50Z/2012,0.22U"	0.22U
C27 C451	120315	"CE0.47U50Z/2012,0.47U"	0.47U
C490	120346	"CE0.33U25Z/2012,0.33/25"	0.33/25
C205	120348	"CE4.7U16M/3216,4.7/16"	4.7/16
C100 C102	120352	"CE100P50J/2012,100P"	100P
C15	120363	"CE180P50J/2012,180P"	180P
C61 C84	120417	"CE0.01U50K/2012,0.01U"	0.01U
"C17 C39 C57 C63			
C65 C67 C69			
C72 C75-76 C82-83			
C88 C94 C97			
C101 C106 C110			
C122 C137 C204			
C207 C220"	120421	"CE0.1U50K/2012,0.1U"	0.1U
ZD1	122227	"ZD/UZ5.1V/0.2W/USC,5.1V 0.2W"	5.1V 0.2W
C107	122241	"CE820P50J/2012,820P"	820P
Q4 Q8 Q19	124670	"NPN/MMBT2222/SOT23,MMBT2222"	MMBT2222
D6 D9 D18 D51-54	125194	"D/SF20LC30,SF20LC30"	SF20LC30
C58 C134 C136	125212	"CE0.1U100K/3216,0.1U100"	0.1U100
C79	125212	"CE0.1U100M/3216,0.1U"	0.1U
C77	125719	"CE0.001U1KK/Y5P/T,0.001/1K"	0.001/1K
C104-105	125720	"CE2200P400M/SD,2200P"	2200P
U8 U10 U15 U401	125843	"KIA431AF/SOT89,KIA431AF"	KIA431AF
C95 C120	125848	"EC100U50M/NXB/T,100/50"	100/50
C8 C48	125849	"EC220U100M/NXA,220/100"	220/100
BD8	125866	"BD/TS15P05G,TS15P05G"	TS15P05G
RLY3-4	125868	"24V/881H-1AH-C/S2L1/2,24V"	24V
R142	125872	"R200KJ/3216,200K"	200K
D12 D35 D37-38 D58	125880	"SD/SS16/SMA,SS16"	SS16
C457	126495	"CE0.001U250J/2012,0.001U"	0.001U
R24	126498	"R2.7KF/2012,2.7K 1%"	2.7K 1%
R11	127195	"R560F/2012,560 1%"	560 1%

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
BD2-3 BD6	127462	"120OHM/BEAD/127462,120ohm"	120ohm
L1-2	127463	"100OHM/BEAD/127463,100ohm"	100ohm
C85 C112	127711	"EC10U50M/NXB/T,10/50"	10/50
F4	128336	"FUSE/178.6165,178.6165"	178.6165
U5	128383	"78R15/KIA/API,78R15"	78R15
C64	129356	"CE10U6.3K/2012,10U6.3"	10U6.3
Q7	129519	"PNP/KTN2907AS/SOT23,KTN2907AS"	KTN2907AS
C125-132	129521	"CE2200P1KM/E/T,2200P1K"	2200P1K
U18	129542	"NJM2403M/DMP08P,NJM2403M"	NJM2403M
C98 C402	130523	"CE220P1KK/Y5R,220P1K"	220P1K
D33	131633	"D/UF5408,UF5408"	UF5408
U3	132173	"TOP242,TOP242"	TOP242
U13	132334	"UCC27324D/SOIC08P/2,UCC27324D"	UCC27324D
U12	132336	"IR2113/SOIC16P/2,IR2113"	IR2113
U7	132340	"UCC25600/SOIC08P/2,UCC25600"	UCC25600
L9-10	132367	"PT/132367,132367"	132367
BK4	132373	"BK/132373,Bracket"	Bracket
BK9-10	132374	"BK/132374,Bracket"	Bracket
"D2 D7 D11 D22-23 D25-27 D30 D34 D36 D39-42 D44-45 D48-50 D55-56 D205"	132384	"SD/US1M/SMA,US1M"	US1M
R16-17	132392	"R1.8MJ/3216,1.8M"	1.8M
R168	132482	"R120KJ/3216,120K"	120K
R169 R459	132483	"R27KJ/3216,27K"	27K
C34-35	132799	"EC470U250M/TDC,470/250"	470/250
Q11 Q401	132801	"N/IPP60R125C6/TO220,IPP60R125C6"	IPP60R125C6
ZD2-5 ZD8	132803	"ZD/18V/MMBZ5248B/SOT23,18V"	18V
T4	132805	"T/132805,132805"	132805
U1	132811	"ICE2PCS03G/SO08P/2,ICE2PCS03G"	ICE2PCS03G
D29	132812	"SD/RFX10TF6S,RFX10TF6S"	RFX10TF6S
Q14	132815	"N/SPP20N60C3/TO220,SPP20N60C3"	SPP20N60C3
C201	132816	"EC10U450M/NFC,10/450"	10/450
C119	132817	"EC220U450M/TDC,220/450"	220/450
C78	132818	"MA0.47U630J/MP,0.47/630(M)"	0.47/630(M)
T2	132819	"T/132819,132819"	132819
T1	132820	"T/132820,132820"	132820
R13 R18	132822	"R3.9MJ/3216,3.9M"	3.9M
R96 R179	132827	"R6.8J/3216,6.8"	6.8
U17	132828	"MIC2778-2BM5/SOT23-5,MIC2778-2BM5"	MIC2778-2BM5
Q1 Q15 Q22 Q26	132830	"NPN/BCP68/SOT223,BCP68"	BCP68
Q12 Q16 Q21 Q25	132831	"PNP/BCP69/SOT223,BCP69"	BCP69
R143	132845	"R680KJ/3216,680K"	680K
R90 R121-123	132849	"R240KJ/3216,240K"	240K
C1-2	132860	"MA0.022U630J/MP,0.022/630(M)"	0.022/630(M)
Q18 Q23	132863	"N/IRFB4332PBF/TO220,IRFB4332PBF"	IRFB4332PBF
C123-124	132883	"MA2.2U250J/MP,2.2/250(M)"	2.2/250(M)
R146	132932	"R430KJ/3216,430K"	430K
BK2	132986	"HS/132986/55,Heat sink"	Heat sink
H32	132987	"HS/132987/55,Heat sink"	Heat sink
H4	132988	"HS/132988/55,Heat sink"	Heat sink
BK7	132989	"HS/132989/55,Heat sink"	Heat sink
T6-7	133090	"PT/133090/24V,133090"	133090
R119	133259	"R5.49KF/2012,5.49K 1%"	5.49K 1%
F2	133284	"ATO/30A/32V/F/UL/133284,30A/32V"	30A/32V
U2	133312	"UCC28220D/SOIC16P/2,UCC28220D"	UCC28220D
L4-5	133335	"6MH/25/CHOKE/LF19-F06M,6mH"	6mH

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
DPA-300D WIRING			
	112598	"FUSE,20MM,T,5A,250V,K/U/CS/J"	FUSE
	113303	"FAN BKT ""R"""	
	113302	"FAN BKT ""L"""	
	114182	DC FAN(3110KL-05W-B70-F04)	MOTOR/FAN
	133089	"DC TERMNAL BLOCK,2P,BI-16PTHC-02P "	CONNECTOR WAFER/TERMINAL
	133389	"CON ASS'Y,FL,16P,5264,5264,AWG26,430mm "	CONNECTOR ASS'Y
	133391	"CON ASS'Y,FL,10P,5264,5264,AWG26,150mm "	CONNECTOR ASS'Y
	133390	"CON ASS'Y,DS,5P,5239,5239,AWG18,150mm "	CONNECTOR ASS'Y
	133388	"CON ASS'Y,FL,5P,5264,5264,AWG26,250mm "	CONNECTOR ASS'Y
DPA-600D AMP			
C102-103 C129-130 C104-105 C108 C131-132 C135	120381	"CE330P50J/2012,330P"	330P
C153-154 C372	120352	"CE100P50J/2012,100P"	100P
C106 C133	127554	"EC2.2U50M/NXB/T,2.2/50"	2.2/50
C107 C134 C201-202 C301-302	120391	"CE470P50J/2012,470P"	470P
C109 C136	133535	"MA0.18U63J/CEM/T,0.18/63(M)"	0.18/63(M)
C110-111 C137-138	120389	"CE47P50J/2012,47P"	47P
"C112-113 C118-119 C139-140 C215 C242 C246-247 C315"	105508	"EC47U25M/RG/T,47/25"	47/25
"C114 C120-125 C141 C145-150 C218 C220 C232 C248-251 C270-271 C318 C332 C370-371 C373"	120421	"CE0.1U50K/2012,0.1U"	0.1U
C115 C127-128 C142 C151-152 C230-231 C330-331	120251	"CE1U50Z/2012,1U"	1U
C116 C143	120349	"CE10P50J/1608,10P"	10P
C117 C144 C228-229 C245 C269 C328-329	120348	"CE4.7U16M/3216,4.7/16"	4.7/16
C126 C239	120247	"CE0.1U50Z/2012,0.1U"	0.1U
C203-206 C303-306	105929	"MA2200P50M/MKS/T,2200P50(M)"	2200P50(M)
C207-208 C307-308	126495	"CE0.001U250J/2012,0.001U"	0.001U
C213-214 C313-314	126715	"EC10U50M/RD,10/50"	10/50
C216-217 C316-317	105910	"MA0.1U250K/DEM/T,0.1/250(M)"	0.1/250(M)
C219	120237	"CE0.001U50J/3216,0.001U"	0.001U
C221	105511	"EC47U50M/SG/T,47/50"	47/50
C223-224 C323-324	105909	"MA0.1U250J/DEM/T,0.1/250(M)"	0.1/250(M)
C225-226 C325-326	105857	"MA0.033U100J/T,0.033/100(M)"	0.033/100(M)
C227 C327	127070	"EC100U10M/SHL/T,100/10 NP"	100/10 NP
C237-238 C255-256 C260-261 C352	126494	"CE0.01U250K/2012,0.01U"	0.01U
C240-241 C243-244 C262-263	105585	"EC470U100M/NXB,470/100"	470/100
C267 C366	129534	"CE0.01U250J/3216,0.01U250"	0.01U250
C292-293 C392-393	105914	"MA0.22U250J/DEM/T,0.22/250(M)"	0.22/250(M)
CN1	111360	"05P/LW-5267/2.5,LW5267-05P"	LW5267-05P
CN101	111371	"16P/LW-5267/2.5,LW5267-16P"	LW5267-16P
CN2	110495	"05P/B5P-VH/3.96/110495,B05PVH-05P"	B05PVH-05P
CN201	111358	"03P/LW-5267/2.5,LW5267-03P"	LW5267-03P

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
CN901	111365	"10P/LW-5267/2.5,LW5267-10P"	LW5267-10P
CON101	128201	"TER/BL/ME030-350/06H/128201,TERMINAL06P"	TERMINAL06P
CON201	132912	"TER/OQ0455510000G/04H/132912,TERMINAL04P"	TERMINAL04P
CP1-3	111330	"02P/53014/2,53014-02P"	53014-02P
D101-102 D105			
D107-108 D111	119196	"D/BAV99/SOT23,BAV99"	BAV99
"D103-104 D106			
D109-110 D112-114			
D204 D211-212 D214			
D219-220 D304 D314			
D901-902"	119190	"D/BAS21/SOT23,BAS21"	BAS21
D205-208 D215-218			
D305-308 D315-318	119203	"D/MURS120T3/DO214AA,MURS120T3"	MURS120T3
D210	127303	"ZD/15V/Z02W/SOT23,15V"	15V
FB1-2 FB201-202			
FB301-302	123776	"80OHM/BEAD/123776,80OHM"	80OHM
FB3	127462	"120OHM/BEAD/127462,120ohm"	120ohm
H4 H16	2001390	"HS/2001390/67,Heat sink"	Heat sink
IC101-106	118730	"NJM072M/DMP08P,NJM072M"	NJM072M
IC201 IC301	131763	"IRS2052MPBF/QFN48P/2,IRS2052MPBF"	IRS2052MPBF
IC202	118724	"7805/KIA/D-PAK,7805"	7805
IC203	129536	"79L05F/KIA/SOT89,KIA79L05F"	KIA79L05F
IC204 IC304	133640	"LM26CIM5-PHA/SOT23-5,LM26CIM5-PHA"	LM26CIM5-PHA
IC205 IC305	128200	"LM26CIM5-TPA/SOT23-5,LM26CIM5-TPA"	LM26CIM5-TPA
IC302	118926	"74HC00/SOP14P,74HC00"	74HC00
L201-202 L301-302	2001369	"24UH/37/2001369,24uH"	24uH
LD101 LD204	119236	"LD/G/1608S/LTST-C190TGKT,LTST-C190TGKT"	LTST-C190TGKT
LD201 LD301	130293	"LD/Y/1608/BL-HKB36A,BL-HKB36A"	BL-HKB36A
LD202 LD302	129968	"LD/R/1608/BL-HUE36A,BL-HUE36A"	BL-HUE36A
Q101-102 Q106-107			
Q208 Q210 Q212 Q218			
Q308 Q310	118672	"NPN/2N3904/SOT23,2N3904"	2N3904
Q103 Q108 Q901			
Q904-905 Q908	129509	"N/PMBFJ112/SOT23,PMBFJ112"	PMBFJ112
"Q104-105 Q109-110			
Q215 Q217			
Q230 Q315 Q317 Q330			
Q902 Q906"	118638	"NPN/KRC403/USM,KRC403"	KRC403
Q201	118643	"NPN/KTC4375-Y/SOT89,KTC4375-Y"	KTC4375-Y
Q204-207 Q304-307	130597	"N/IRFB5620PBF/TO220,IRFB5620PBF"	IRFB5620PBF
Q211	118627	"PNP/KRA303/USM,KRA303"	KRA303
Q213	118657	"PNP/KTA1666/SOT89,KTA1666"	KTA1666
Q214 Q216 Q219			
Q314 Q316 Q319	118663	"PNP/2N3906S/SOT23,2N3906S"	2N3906S
R101-102 R128-129	119455	"R1.8KJ/2012,1.8K"	1.8K
"R105-106 R114-117			
R132-133 R141-144			
R225-226 R284			
R295 R297 R325-326			
R351-353			
R397 R905-906			
R912-913"	119367	"R10KJ/2012,10K"	10K
R107 R125 R134 R151			
R246 R346 R901 R908	119605	"R3.9KJ/2012,3.9K"	3.9K
R108 R110 R135 R137			
R902 R909	119499	"R22KJ/2012,22K"	22K
R109 R111 R136 R138	119473	"R2KJ/2012,2K"	2K

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
R112 R139	119949	"R4.3KJ/2012,4.3K"	4.3K
R113 R140	119580	"R33KJ/2012,33K"	33K
R118 R123 R145 R149			
R155-158 R907 R914	119370	"R100KJ/2012,100K"	100K
"R120 R127 R146			
R153 R209-210 R265			
R286 R288 R293			
R309-310 R386 R388			
R393"	119630	"R47KJ/2012,47K"	47K
R121 R147	119466	"R180KJ/2012,180K"	180K
"R122 R126 R148			
R152 R201-202			
R211-212 R248 R272			
R278 R301-302			
R311-312 R348 R372"	119362	"R1KJ/2012,1K"	1K
R154 R223-224			
R323-324	119590	"R3.6KJ/2012,3.6K"	3.6K
R159-160	119401	"R12KJ/2012,12K"	12K
R170-171 R279-280			
R381	104234	"R10J/A,10"	10
R203-204 R294			
R303-304	119548	"R3KJ/2012,3K"	3K
R213-214 R313-314	119420	"R150J/2012,150"	150
R215-216 R241			
R256 R315-316			
R341 R356	119353	"R100J/2012,100"	100
R219-220 R319-320	104274	"R2KJ/A,2K"	2K
R221-222 R271			
R321-322 R371	119707	"R6.8KJ/2012,6.8K"	6.8K
R227-228 R327-328	104347	"R56KJ/A,56K"	56K
R229-232 R282-283			
R329-332 R382-383	119645	"R4.7J/2012,4.7"	4.7
R233-236 R333-336	119346	"R10J/2012,10"	10
R237-238 R337-338	104454	"R10J/1W/MF/T,10 1W"	10 1W
R240 R243 R250 R340			
R343 R350	119670	"R560J/2012,560"	560
R242 R266 R342	119576	"R3.3KJ/2012,3.3K"	3.3K
R247 R347	119689	"R6.2KJ/2012,6.2K"	6.2K
R264 R285 R287			
R292 R385 R387 R392	119625	"R4.7KJ/2012,4.7K"	4.7K
R267-268	104673	"R56J/2W/MO/T,56 2W"	56 2W
R269-270 R369-370	119405	"R120KJ/2012,120K"	120K
R274-275 R374-375	104745	"R25J/5W/CE,25"	25
R276-277 R376-377	129577	"R4.7KJ/2W/MF/T,4.7K 2W"	4.7K 2W
R290 R390	119617	"R47J/2012,47"	47
R296	119502	"R220KJ/2012,220K"	220K
R3 R103-104 R124			
R130-131 R150			
R244-245 R344-345	119747	"R8.2KJ/2012,8.2K"	8.2K
R903 R910	119435	"R150KJ/2012,150K"	150K
R904 R911	119635	"R470KJ/2012,470K"	470K
SW201	112022	"SL/JSS-2208A,JSS-2208A"	JSS-2208A
"TP106 TP111			
TP205-207 TP209			
TP305-307 TP310			
TP312"	106871	"TP/TP00325-21/T,TP00325-21"	TP00325-211

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
DPA-600D FRONT			
AN1002 CN1001	133349	"05P/ASSY/2.5/133349,ASS'Y-05P"	ASS'Y-05P
AN101	111371	"16P/LW-5267/2.5,LW5267-16P"	LW5267-16P
AN901	111365	"10P/LW-5267/2.5,LW5267-10P"	LW5267-10P
BK1-2	113528	"BK/113528,Bracket"	Bracket
C1-2	120348	"CE4.7U16M/3216,4.7/16"	4.7/16
C13-14 C903-904 C908	120352	"CE100P50J/2012,100P"	100P
C17-20 C25-26			
C909-910 C1001	120421	"CE0.1U50K/2012,0.1U"	0.1U
C5-6 C906	133535	"MA0.18U63J/CEM/T,0.18/63(M)"	0.18/63(M)
C901-902	120381	"CE330P50J/2012,330P"	330P
C905	127554	"EC2.2U50M/NXB/T,2.2/50"	2.2/50
C9-10 C907	120391	"CE470P50J/2012,470P"	470P
C911	126494	"CE0.01U250K/2012,0.01U"	0.01U
CN1002	111360	"05P/LW-5267/2.5,LW5267-05P"	LW5267-05P
CON901	130135	"TER/OQ0812510000G/08H/130135,TERMINAL08P"	TERMINAL08P
D1-2 D901-906			
D1001-1003	119196	"D/BAV99/SOT23,BAV99"	BAV99
D5-8	119190	"D/BAS21/SOT23,BAS21"	BAS21
IC1-2 IC901	118730	"NJM072M/DMP08P,NJM072M"	NJM072M
IC902	103384	"PC/LTV847,LTV847"	LTV847
LD1 LD5	129892	"LD/R/3T/BL-B4541,BL-B4541"	BL-B4541
LD1004	126148	"LD/B/3T/SLB1381N-UZ,SLB1381N-UZ"	SLB1381N-UZ
LD2 LD6 LD1002	130016	"LD/Y/3T/BL-3141-AA-AV,BL-3141-AA-AV"	BL-3141-AA-AV
LD3-4 LD7-8 LD1001			
LD1003	130018	"LD/G/3.1T/BL-B2141,BL-B2141-AA-AV-T05"	BL-B2141-AA-AV-T05
LD901-904	130293	"LD/Y/1608/BL-HKB36A,BL-HKB36A"	BL-HKB36A
LIM101-103	114982	"LIMITER/5.5/11.5/114982,11.5mm"	11.5mm
LIM107	114985	"LIMITER/5.5/8/114985,8mm"	8mm
LIM1-8	114983	"LIMITER/5.5/14.7/114983,14.7mm"	14.7mm
Q1-4 Q13-18 Q25-26			
Q901-904 Q1001-1002	118663	"PNP/2N3906S/SOT23,2N3906S"	2N3906S
Q9-10	118672	"NPN/2N3904/SOT23,2N3904"	2N3904
R1003 R1006	119495	"R2.2KF/3216,2.2K 1%"	2.2K 1%
R1004	119620	"R470J/2012,470"	470
R1-2 R25-26 R908	119580	"R33KJ/2012,33K"	33K
R13-14	119366	"R10KJ/1608,10K"	10K
R17-18	119711	"R68KJ/2012,68K"	68K
R21-22 R907	119362	"R1KJ/2012,1K"	1K
R29-30 R909	119605	"R3.9KJ/2012,3.9K"	3.9K
R37-38 R1001	119393	"R120J/2012,120"	120
R45-46 R920 R922			
R924 R926	119630	"R47KJ/2012,47K"	47K
R49-50 R905-906	119367	"R10KJ/2012,10K"	10K
R5-6 R41-42 R1002	119499	"R22KJ/2012,22K"	22K
R901-902	119455	"R1.8KJ/2012,1.8K"	1.8K
R903-904	119747	"R8.2KJ/2012,8.2K"	8.2K
R9-10 R33-34 R910	119401	"R12KJ/2012,12K"	12K
R911-914	119527	"R2.7KJ/2012,2.7K"	2.7K
R915-918	119548	"R3KJ/2012,3K"	3K
R919 R921 R923 R925	119625	"R4.7KJ/2012,4.7K"	4.7K
SW1	112178	"PW/SDDL1PASL051,SDDL1PASL051"	SDDL1PASL051
VR1-2	105055	"203A/09/RK09K11N0005,20KA"	20KA
VR901	104992	"203A/09/RK09S1110011,20KA"	20KA
DPA-600D SMPS			
BD2-3 BD6	127462	"120OHM/BEAD/127462,120ohm"	120ohm

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
BD8	125866	"BD/TS15P05G,TS15P05G"	TS15P05G
BK2	132986	"HS/132986/55,Heat sink"	Heat sink
BK4	132373	"BK/132373,Bracket"	Bracket
BK7	132989	"HS/132989/55,Heat sink"	Heat sink
BK9-10	132374	"BK/132374,Bracket"	Bracket
C100 C102	120352	"CE100P50J/2012,100P"	100P
C104-105	125720	"CE2200P400M/SD,2200P"	2200P
C108	120283	"CE0.22U50Z/2012,0.22U"	0.22U
C109	120275	"CE2200P50K/2012,2200P"	2200P
C115	120247	"CE0.1U50Z/2012,0.1U"	0.1U
C117	105825	"MA0.1U200J/T,0.1/200(M)"	0.1/200(M)
C118	120235	"CE0.001U50J/2012,0.001U"	0.001U
C119	132817	"EC220U450M/TDC,220/450"	220/450
C1-2	132860	"MA0.022U630J/MP,0.022/630(M)"	0.022/630(M)
C121	105548	"EC4.7U50M/RG/T,4.7/50"	4.7/50
C123-124 C139-140	132883	"MA2.2U250J/MP,2.2/250(M)"	2.2/250(M)
C125-132	129521	"CE2200P1KM/E/T,2200P1K"	2200P1K
C15	120363	"CE180P50J/2012,180P"	180P
"C17 C39 C57 C63 C65 C67 C69 C72 C75-76 C82-83 C88 C94 C97 C101 C106 C110 C122 C137 C204 C207 C220"	120421	"CE0.1U50K/2012,0.1U"	0.1U
C201	132816	"EC10U450M/NFC,10/450"	10/450
C203 C206	105508	"EC47U25M/RG/T,47/25"	47/25
C205	120348	"CE4.7U16M/3216,4.7/16"	4.7/16
C27 C451	120315	"CE0.47U50Z/2012,0.47U"	0.47U
C34-35	132799	"EC470U250M/TDC,470/250"	470/250
C4 C7 C11 C14 C55 C70 C73 C81	105462	"EC22U25M/RG/T,22/25"	22/25
C455-456	105909	"MA0.1U250J/DEM/T,0.1/250(M)"	0.1/250(M)
C457	126495	"CE0.001U250J/2012,0.001U"	0.001U
C46 C202	105793	"CE2200P250M/AC,2200P250"	2200P250
C461	105933	"MA3900P250J/CEM/T,3900P250(M)"	3900P250(M)
C490	120346	"CE0.33U25Z/2012,0.33/25"	0.33/25
"C5-6 C31-32 C49 C86-87 C96 C111 C114 C133"	120251	"CE1U50Z/2012,1U"	1U
C58 C134 C136	125212	"CE0.1U100K/3216,0.1U100"	0.1U100
C61 C84	120417	"CE0.01U50K/2012,0.01U"	0.01U
C62 C66 C68	105351	"EC220U50M/RD,220/50"	220/50
C64	129356	"CE10U6.3K/2012,10U6.3"	10U6.3
C71 C103 C113 C116	105625	"EC2200U35M/RD,2200/35"	2200/35
C74	105463	"EC22U50M/SHL/T,22/50"	22/50
C77	125719	"CE0.001U1KK/Y5P/T,0.001/1K"	0.001/1K
C78	132818	"MA0.47U630J/MP,0.47/630(M)"	0.47/630(M)
C79	125212	"CE0.1U100M/3216,0.1U"	0.1U
C8 C48	125849	"EC220U100M/NXA,220/100"	220/100
C85 C112	127711	"EC10U50M/NXB/T,10/50"	10/50
C95 C120	125848	"EC100U50M/NXB/T,100/50"	100/50
C98 C402	130523	"CE220P1KK/Y5R,220P1K"	220P1K
CN1-2	111360	"05P/LW-5267/2.5,LW5267-05P"	LW5267-05P
CN4	110850	"TER/BL/010/02H/110850,TERMINAL02P"	TERMINAL02P
CN5	110495	"05P/B5P-VH/3.96/110495,B05PVH-05P"	B05PVH-05P
CX1 CX3	105992	"MA1U275K/AC,1/275(M)"	1/275(M)
D1 D10 D46-47	119171	"D/1N4148/SOT23,1N4148"	1N4148

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
D12 D35 D37-38			
D57-59	125880	"SD/SS16/SMA,SS16"	SS16
"D2 D7 D11 D22-23			
D25-27			
D30 D34 D36 D39-42			
D44-45 D48-50			
D55-56 D205"	132384	"SD/US1M/SMA,US1M"	US1M
D204	119210	"ZD/10V/BZX84C/SOT23,10V"	10V
D21 D43	119194	"D/KDS184/SOT23,KDS184"	KDS184
D29	132812	"SD/RFX10TF6S,RFX10TF6S"	RFX10TF6S
D33	131633	"D/UF5408,UF5408"	UF5408
D6 D9 D18 D51-54	125194	"D/SF20LC30,SF20LC30"	SF20LC30
F1	112598	"20/5A/250V/T/KUCJ/112598,T5A/250V"	T5A/250V
F2	133284	"ATO/30A/32V/F/UL/133284,30A/32V"	30A/32V
F3	111579	"FUSE/GF-205B,GF-205B"	GF-205B
F4	128336	"FUSE/178.6165,178.6165"	178.6165
H2	133697	"HS/133215/55,Heat sink"	Heat sink
H32	132987	"HS/132987/55,Heat sink"	Heat sink
JK1	111737	"ACIN/SS-7B-1-09,AC IN"	AC IN
L1-2	127463	"100OHM/BEAD/127463,100ohm"	100ohm
L4-5	133335	"6MH/25/CHOKE/LF19-F06M,6mH"	6mH
L9-10	132367	"PT/132367,132367"	132367
PC1-6 PC9 PC16	118872	"PC/LTV817B,LTV817B"	LTV817B
Q1 Q15 Q22 Q26	132830	"NPN/BCP68/SOT223,BCP68"	BCP68
Q11 Q14 Q401	132801	"N/IPP60R125C6/TO220,IPP60R125C6"	IPP60R125C6
Q12 Q16 Q21 Q25	132831	"PNP/BCP69/SOT223,BCP69"	BCP69
Q13	118627	"PNP/KRA303/USM,KRA303"	KRA303
Q17-18 Q23-24	132863	"N/IRFB4332PBF/TO220,IRFB4332PBF"	IRFB4332PBF
Q20	118657	"PNP/KTA1666/SOT89,KTA1666"	KTA1666
Q4 Q8 Q19	124670	"NPN/MMBT2222/SOT23,MMBT2222"	MMBT2222
Q7	129519	"PNP/KTN2907AS/SOT23,KTN2907AS"	KTN2907AS
R10 R110	119576	"R3.3KJ/2012,3.3K"	3.3K
R100 R111	104543	"R0.1J/3W/MO,0.1 3W"	0.1 3W
R103	119822	"R68KF/3216,68K 1%"	68K 1%
R104	119732	"R7.5KJ/2012,7.5K"	7.5K
R105	119689	"R6.2KJ/2012,6.2K"	6.2K
R11	127195	"R560F/2012,560 1%"	560 1%
R113	119405	"R120KJ/2012,120K"	120K
R114	119492	"R220J/2012,220"	220
R117	119644	"R4.7J/3216,4.7"	4.7
R118 R176 R183			
R402 R404	119955	"R51J/2012,51"	51
R119	133259	"R5.49KF/2012,5.49K 1%"	5.49K 1%
R124 R126-127			
R132-133 R159	119473	"R2KJ/2012,2K"	2K
R125	119658	"R51KJ/2012,51K"	51K
R128 R140	119436	"R150KJ/3216,150K"	150K
R13 R18	132822	"R3.9MJ/3216,3.9M"	3.9M
R142	125872	"R200KJ/3216,200K"	200K
R143	132845	"R680KJ/3216,680K"	680K
R146	132932	"R430KJ/3216,430K"	430K
R147 R150	119341	"R1J/3216,1"	1
R15 R79	119401	"R12KJ/2012,12K"	12K
R152	119727	"R750J/2012,750"	750
R155	119425	"R1.5KJ/3216,1.5K"	1.5K
R158	119548	"R3KJ/2012,3K"	3K
R160-161 R164-167	104592	"R220J/2W/MO/T,220 2W"	220 2W

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
R16-17	132392	"R1.8MJ/3216,1.8M"	1.8M
R168	132482	"R120KJ/3216,120K"	120K
R169 R459	132483	"R27KJ/3216,27K"	27K
R174	119770	"R100KF/3216,100K 1%"	100K 1%
R19-20 R203-204	119631	"R47KJ/3216,47K"	47K
"R2 R66-67 R73 R89			
R108 R129 R134 R136			
R154 R177 R181 R403			
R405 R461"	119367	"R10KJ/2012,10K"	10K
R201-202	119374	"R1MJ/3216,1M"	1M
R205	119487	"R22J/2012,22"	22
R206	119670	"R560J/2012,560"	560
R24	126498	"R2.7KF/2012,2.7K 1%"	2.7K 1%
R25	119499	"R22KJ/2012,22K"	22K
R27	119462	"R18KJ/2012,18K"	18K
R3 R5	104518	"R10J/2W/MO/T,10 2W"	10 2W
R33-34	119581	"R33KJ/3216,33K"	33K
R36 R56 R156 R207	119346	"R10J/2012,10"	10
R40 R71 R80 R171			
R178 R180 R409	120063	"R0J/3216,0"	0
R463	119408	"R1.3KF/2012,1.3K 1%"	1.3K 1%
R469	119625	"R4.7KJ/2012,4.7K"	4.7K
R471	104567	"R15KJ/1W/MO/T,15K 1W"	15K 1W
R48 R61	119388	"R12J/2012,12"	12
R54 R144-145	119636	"R470KJ/3216,470K"	470K
R57	104453	"R750KJ/1/2W/MF/A,750K 1/2W"	750K 1/2W
R63 R175	119348	"R10J/3216,10"	10
R64	119701	"R680J/2012,680"	680
R68 R130 R172	119655	"R5.1KJ/2012,5.1K"	5.1K
R69 R138-139			
R148-149	119362	"R1KJ/2012,1K"	1K
R70	119353	"R100J/2012,100"	100
R72	104634	"R330J/2W/MO/T,330 2W"	330 2W
R76 R116 R462	119396	"R1.2KJ/2012,1.2K"	1.2K
R77 R97-98 R115			
R162-163	104537	"R10KJ/2W/MO/T,10K 2W"	10K 2W
R78	119373	"R1MJ/2012,1M"	1M
R7-8 R137	119630	"R47KJ/2012,47K"	47K
R82 R101	119497	"R2.2KJ/2012,2.2K"	2.2K
R87	119823	"R75KF/2012,75K 1%"	75K 1%
R90 R121-123	132849	"R240KJ/3216,240K"	240K
R91	119476	"R20KJ/2012,20K"	20K
R92 R131 R135 R490	119428	"R15KJ/2012,15K"	15K
R93	119586	"R330KJ/2012,330K"	330K
R96 R173 R179 R182	132827	"R6.8J/3216,6.8"	6.8
R99	119408	"R1.3KJ/2012,1.3K"	1.3K
RLY3-4	125868	"24V/881H-1AH-C/S2L1/2,24V"	24V
T1	132820	"T/132820,132820"	132820
T2	132819	"T/132819,132819"	132819
T4	132805	"T/132805,132805"	132805
T6-7	133090	"PT/133090/24V,133090"	133090
TH1	103435	"10/M/10A/160T/-40~180C/DSC-10D-30,10 ohm"	10 ohm
TP1-10 TP16 TP19			
TP201 TP209	106871	"TP/TP00325-21/T,TP00325-21"	TP00325-21
U1	133674	"ICE2PCS02G/SO08P/2,ICE2PCS02G"	ICE2PCS02G
U12	132336	"IR2113/SOIC16P/2,IR2113"	IR2113
U13	132334	"UCC27324D/SOIC08P/2,UCC27324D"	UCC27324D

ELECTRICAL PARTS LIST

REF	ITEM NO.	DEFINE	VALUE
U17	132828	"MIC2778-2BM5/SOT23-5,MIC2778-2BM5"	MIC2778-2BM5
U18	129542	"NJM2403M/DMP08P,NJM2403M"	NJM2403M
U2	133312	"UCC28220D/SOIC16P/2,UCC28220D"	UCC28220D
U3	132173	"TOP242,TOP242"	TOP242
U5	128383	"78R15/KIA/API,78R15"	78R15
U7	132340	"UCC25600/SOIC08P/2,UCC25600"	UCC25600
U8 U10 U15 U401	125843	"KIA431AF/SOT89,KIA431AF"	KIA431AF
U9	103061	"7812/KIA,7812"	7812
VAR1-2	103422	"ZNR/361/INR14D361,360V"	360V
ZD1	122227	"ZD/UZ5.1V/0.2W/USC,5.1V 0.2W"	5.1V 0.2W
ZD2-6 ZD8 ZD11	132803	"ZD/18V/MMBZ5248B/SOT23,18V"	18V
DPA-600D WIRING			
	133175	"FUSE,0215015.MXP"	FUSE
	113303	"FAN BKT ""R"""	
	113302	"FAN BKT ""L"""	
	114182	DC FAN(3110KL-05W-B70-F04	MOTOR/FAN
	109889	"CON ASS'Y,DS,1P,250T08,250T08,80MM"	CONNECTOR ASS'Y
	133388	"CON ASS'Y,FL,5P,5264,5264,AWG26,250mm"	CONNECTOR ASS'Y
	133389	"CON ASS'Y,FL,16P,5264,5264,AWG26,430mm"	CONNECTOR ASS'Y
	133390	"CON ASS'Y,DS,5P,5239,5239,AWG18,150mm"	CONNECTOR ASS'Y
	133391	"CON ASS'Y,FL,10P,5264,5264,AWG26,150mm"	CONNECTOR ASS'Y
	133089	"DC TERMNAL BLOCK,2P,BI-16PTHC-02P"	CONNECTOR WAFER/TERMINAL

TOP & BOTTOM VIEW OF P.C BOARD

DPA-300D AMP



TOP & BOTTOM VIEW OF P.C BOARD

DPA-300D AMP



TOP & BOTTOM VIEW OF P.C BOARD

DPA-300D FRONT



TOP & BOTTOM VIEW OF P.C BOARD

DPA-300D FRONT



TOP & BOTTOM VIEW OF P.C BOARD

DPA-300D SMPS



TOP & BOTTOM VIEW OF P.C BOARD

DPA-300D SMPS



TOP & BOTTOM VIEW OF P.C BOARD

DPA-600D AMP



TOP & BOTTOM VIEW OF P.C BOARD

DPA-600D AMP



TOP & BOTTOM VIEW OF P.C BOARD

DPA-600D FRONT



TOP & BOTTOM VIEW OF P.C BOARD

DPA-600D FRONT



TOP & BOTTOM VIEW OF P.C BOARD

DPA-600D SMPS



TOP & BOTTOM VIEW OF P.C BOARD

DPA-600D SMPS



BLOCK DIAGRAM

DPA-300D



BLOCK DIAGRAM

DPA-600D



DPA-300D AMP



SCHEMATIC DIAGRAM

DPA-300D AMP



DPA-300D AMP



SCHEMATIC DIAGRAM

DPA-300D FRONT



DPA-300D SMPS



SCHEMATIC DIAGRAM

DPA-300D SMPS



DPA-300D SMPS



SCHEMATIC DIAGRAM

DPA-600D AMP



DPA-600D AMP


Speaker out
DC FAN
Heat Sink
Unique parts by models
model 300D
model 600D
L301, L302
L301, L302
C390, C391
C390, C391
C392, C393
C392, C393

SCHEMATIC DIAGRAM

DPA-600D AMP



DPA-600D FRONT



SCHEMATIC DIAGRAM

DPA-600D FRONT



DPA-600D FRONT



SCHEMATIC DIAGRAM

DPA-600D FRONT



DPA-600D SMPS



SCHEMATIC DIAGRAM

DPA-600D SMPS



WIRING DIAGRAM

DPA-300D



WIRING DIAGRAM



NOTE

EXPLODED VIEW OF CABINET &
CHASSIS/MECHANICAL PARTS LIST

DPA-300D



EXPLODE VIEW_DPA-300D (R)

NO	PART NAME	PART NUMBER	Q'TY	REMARKS
S19	NUT FLANG M4	114595	2	
S18	SCREW BM 4X8BK	114292	2	
S17	SCREW 3BTC 3X6B	114487	8	
S16	SCREW ASS'Y PM 4X8N	114412	4	
S15	SCREW BM 3X6N	114281	4	
S14	SCREW BM 3X6N	114281	8	
S13	ASS'Y SCREW PM 3X12N	130772	11	
S12	SCREW ASS'Y PM 4X8N	114412	2	
S11	SCREW BM 4X8BK	114292	4	
S10	SCREW 3BTC 4X14B	114501	2	
S9	SCREW 3BTC 4X8BK	114497	4	
S8	SCREW BM 3X6B	114280	2	
S7	SCREW 2BTC 3X8B	114465	2	
S6	SCREW WSAM 4X6N	114567	1	
S5	SCREW 2BTC 4X12B	114477	4	
S4	SCREW BM 3X6N	114281	2	
S3	SCREW 2BTC 3X8B	114465	4	
S2	SCREW BM 4X12B	114297	4	
S1	SCREW 3BTC 3X6B	114487	6	
35				
34				
33	TRANS		1	
32	LED LIMITER	114985	1	(H=8mm)
31	TOP COVER	100469	1	
30	BRACKET PCB	113528	2	
29	PRIORITY B'D		1	
28	BKT FAN "R"	113303	1	
27	FAN BKT "L"	113302	1	
26	FAN		1	
25	AMP B'D		1	
24	TR BKT	132433	2	
23	TR BKT	113431	1	
22	AC BKT	132374	2	
21	SHIELD COVER	132373	1	
20	AC INLET		1	
19	SMPS B'D		1	
18	INSULATION SHEET	133409	1	
17	AC TERMINAL		1	
16	B.K.T(Q-1000,COM)	100798	2	
15	FOOT	114114	2	
14	MAIN CHASSIS (DPA-300D)	132347	1	
13	POWER SW B'D		1	
12	STBY B'D		1	
11	LED LIMITER	114982	3	(H=11.5mm)
10	FRONT B'D		1	
9	LED LIMITER	114983	8	(H=14.7mm)
8	LED SPONGE	132370	2	
7	LED LENS	132369	2	
6	VR KNOB	124749	2	
5	BEZZEL PUSH	114705	1	
4	PUSH KNOB	114868	1	
3	GUIDE HANDLE	114879	2	
2	PANEL FRONT (DPA-300D)	2001318	1	
1	HANDLE,2U,BLACK	127710	2	

EXPLODED VIEW OF CABINET &
CHASSIS/MECHANICAL PARTS LIST

DPA-600D



EXPLODE VIEW_DPA-600D (R)

NO	PART NAME	PART NUMBER	Q'TY	REMARKS
S19	NUT FLANG M4	114595	2	
S18	SCREW BM 4X8BK	114292	2	
S17	SCREW 3BTC 3X6B	114487	8	
S16	SCREW ASS'Y PM 4X8N	114412	4	
S15	SCREW BM 3X6N	114281	4	
S14	SCREW BM 3X6N	114281	8	
S13	ASS'Y SCREW PM 3X12N	130772	11	
S12	SCREW ASS'Y PM 4X8N	114412	2	
S11	SCREW BM 4X8BK	114292	4	
S10	SCREW 3BTC 4X14B	114501	2	
S9	SCREW 3BTC 4X8BK	114497	4	
S8	SCREW BM 3X6B	114280	2	
S7	SCREW 2BTC 3X8B	114465	2	
S6	SCREW WSAM 4X6N	114567	1	
S5	SCREW 2BTC 4X12B	114477	4	
S4	SCREW BM 3X6N	114281	2	
S3	SCREW 2BTC 3X8B	114465	4	
S2	SCREW BM 4X12B	114297	4	
S1	SCREW 3BTC 3X6B	114487	6	
35				
34				
33	TRANS		1	
32	LED LIMITER	114985	1	(H=8mm)
31	TOP COVER	100469	1	
30	BRACKET PCB	113528	2	
29	PRIORITY B'D		1	
28	BKT FAN "R"	113303	1	
27	FAN BKT "L"	113302	1	
26	FAN		1	
25	AMP B'D		1	
24	TR BKT	132433	4	
23	TR BKT	113431	1	
22	AC BKT	132374	2	
21	SHIELD COVER	132373	1	
20	AC INLET		1	
19	SMPS B'D		1	
18	INSULATION SHEET	133411	1	
17	AC TERMINAL		1	
16	B.K.T(Q-1000.COM)	100798	2	
15	FOOT	114114	2	
14	MAIN CHASSIS (DPA-600D)	132348	1	
13	POWER SW B'D		1	
12	STBY B'D		1	
11	LED LIMITER	114982	3	(H=11.5mm)
10	FRONT B'D		1	
9	LED LIMITER	114983	8	(H=14.7mm)
8	LED SPONGE	132370	2	
7	LED LENS	132369	2	
6	VR KNOB	124749	2	
5	BEZZEL PUSH	114705	1	
4	PUSH KNOB	114868	1	
3	GUIDE HANDLE	114879	2	
2	PANEL FRONT (DPA-600D)	2001319	1	
1	HANDLE,2U,BLACK	127710	2	

www.inter-m.com
MADE IN KOREA
2014. 1