

SERVICE

MANUAL

REMOTE AMPLIFIER WITH ZONE

SELECTOR

RM-916

interM

ELECTRICAL PARTS LIST (RM-916)

| Ref No. | Part No. | Description | Value | Qty |
|---|--------------|--------------------------------|----------------|-----|
| MAIN B'D | | | | |
| IC205 | 2128740208 | IC BXA 4240 | BXA4240 | 1 |
| C202 | 3509104530-T | CAP CE F 0.1UF 50V Z | 104(CE) | 1 |
| C312 C307 C319 C342 C344 | 3509220130-T | CAP CE SL 22PF 50V J | 22P | 5 |
| C338 | 3609104120-T | CAP MA 0.1UF 100V J | 104(M) | 1 |
| C324 C329 | 3509470130-T | CAP CE SL 47PF 50V J | 47P | 2 |
| C201 | 3409222171-T | CAP AF RSG 220UF 50V SG 10 P | 220/50V | 1 |
| C301 C304-306 C321 C317-318 C325 C328 C331-333 C335 C341 | 3409247071-T | CAP AF RSG 47UF 50V 6 P | 47/50 | 14 |
| C316 C310 C343 C334 | 3409210071-T | CAP AF RSG 10UF 50V 5 P | 10/50 | 5 |
| C336 C339-340 | 3409247971-T | CAP AF RSG 4.7UF 50V 5 P | 4.7/50 | 3 |
| IC204 | 2118032210 | IC TA7666P TOSHIBA(2281) | KA 2181 | 1 |
| IC201-202 IC206 | 2118010590 | IC NJM4558D JRC | 4558 | 3 |
| IC203 | 2118010332 | IC NJM 5532DD JRC | 5532 | 1 |
| D101 D103-104 | 2058100996 | DIODE RECTIFIER LT1N4006(4007) | IN4006 | 3 |
| J1 | 4438193810 | XLR JACK(F) 3P(E203A0040N) | XLR JACK INPUT | 1 |
| JP1-24 | | | JUMPER1 | 24 |
| LD101-117 LD119 LD121-125 LD131 | 2300032100 | LED LTL-1CHG LITEON | LED GREEN | 24 |
| LD126-129 | 2318999990 | LED DISPLAY A43B/5G4YH | LED DISPLAY | 4 |
| LD130 LD118 | 2300030100 | LED LTL-1CHE LITEON | LED RED | 2 |
| R201 | 3039479572-F | RES MO 4.7 2W J N | 4.7/2W | 1 |
| R101-118 R368 | 3009332973 | RES CF 3.3K 1/5W J N | 3.3K | 19 |
| R350 | 3009183973 | RES CF 18K 1/5W J N | 18K | 1 |
| R351 R349 | 3009273973 | RES CF 27K 1/5W J N | 27K | 2 |
| R353 | 3009333973 | RES CF 33K 1/5W J N | 33K | 1 |
| R322 R354-363 | 3009122973 | RES CF 1.2K 1/5W J N | 1.2K | 11 |
| R352 | 3009153973 | RES CF 15K 1/5W J N | 15K | 1 |
| R364-365 | 3009104973 | RES CF 100K 1/5W J N | 100K | 2 |
| R366 | 3009155973 | RES CF 1.5M 1/5W J N | 1.5M | 1 |
| R367 | 3009103973 | RES CF 10K 1/5W J N | 10K | 1 |
| R301 | 3009151973 | RES CF 150 1/5W J N | 150 | 1 |
| R302 R304 | 3009123973 | RES CF 12K 1/5W J N | 12K | 2 |
| R303 R305 R308-309 R329-330 R333-335 R342 | 3009103973 | RES CF 10K 1/5W J N | 10K | 10 |
| R314 R317-318 R320 R323-324 R327-328 R331-332 R313 R344-346 R371-372 R375-376 | 3009104973 | RES CF 100K 1/5W J N | 100K | 18 |
| R316 R326 | 3009243973 | RES CF 24K 1/5W JN CDC-9300 | 24K | 2 |
| R311 R310 R315 | 3009473973 | RES CF 47K 1/5W J N | 47K | 3 |
| R336-337 | 3009820973 | RES CF 82 1/5W J N | 82 | 2 |
| R341 R370 R373-374 R377 | 3009472973 | RES CF 4.7K 1/5W J N | 4.7K | 5 |

| | | | | |
|---|--------------|------------------------------|----------------|----|
| R340 R343 | 3009222973 | RES CF 2.2K 1/5W J N | 2.2K | 2 |
| R319 | 3009101973 | RES CF 100 1/5W J N | 100 | 1 |
| R321 | 3009303973 | RES CF 30K 1/5W J N | 30K | 1 |
| R306-307 | 3009471973 | RES CF 470 1/5W J N | 470 | 2 |
| R325 | 3009203973 | RES CF 20K 1/5W J N | 20K | 1 |
| R369 | 3009121973 | RES CF 120 1/5W J N | 120 | 1 |
| R312 | 3009272973 | RES CF 2.7K 1/5W J N | 2.7K | 1 |
| RL101 | 5528999700 | RELAY 876AN2-2C-S 24VDC | RY24V | 1 |
| SW30 | 4648099310 | POWER SWITCH (H8500VB) | POWER SW | 1 |
| Q201-204 | 2008606998-T | KTD1302-AT | D1302 | 4 |
| VR101-103 | 3228068710 | VR RK09K1130D0N | 20KA | 3 |
| CN6 CN101 | 4428595002 | LW5267/LWB0640/2.5MM-02P | WAFER2P | 2 |
| CN102 | 4428595003 | LW5267/LWB0640/2.5MM-03P | WAFER3P | 1 |
| ZD201 | 2058502120 | DIODE ZENER UZ-12BM(1N5242B) | 12BM | 1 |
| ZD202 | 2058500051 | DIODE ZENER UZ-5.1B(1N5231B) | 5.1BM | 1 |
| SW2 | | | SW/PUSH | 1 |
| SW4 | | | SW 2285 NL () | 1 |
| SW1 SW3 | | | SW 2285 L () | 2 |
| SW118 | | | SW 2281 (ALL) | 1 |
| AN4 | | | CON17P | 1 |
| CN4 | | | WAFER17P | 1 |
| AN6 AN101 | | | CON2P | 2 |
| AN12 AN102 | | | CON3P | 2 |
| C302-303 C315 | | | 100P | 3 |
| C322-323 C326-327 C313 C330 C314 C308-309 C320 C345 | | | 22/50 | 11 |
| IC101 | | | IC 7812 | 1 |
| R347 | | | 150/2W | 1 |
| R348 | | | 1K/2W | 1 |
| | 3009561973 | RES CF 560 1/5W J N | 560R | 1 |
| | 3009273973 | RES CF 27K 1/5W J N | 27K | 2 |
| | 2008606104-T | TR NPN KTC3198-Y-AT TO-92 | C 3198Y | 2 |
| | 3409210141-T | CAP AF RSG 100UF 25V 6 P | E 100/25V | 11 |

| | | | | | | | | | | | |
|---------------|----------|-----------|-------------------------|----|----|------|-------|---------|----------|------|------------------------------------|
| 1 | | 2 | | 3 | | 4 | | 5 | | 6 | |
| COMPANY | INTER.M | APPLICANT | REVISED NUMBER AND DATE | | | SIGN | DRAWN | CHECKED | APPROVED | NOTE | SCHEMATIC DIAGRAM MODEL: RM-916 |
| TYPE CODE | | | 1. | 4. | 7. | | | | | | |
| APPROVED DATE | 99.04.16 | | 2. | 5. | 8. | | | | | | |
| | | | 3. | 6. | 9. | | | | | | SIZE: A3 SHEET NO.: 1/1 |

